

USING WITH NOKIA 8910i

SUGGESTED PAIRING MODES: HANDSFREE PAIRING MODE

Press the multi-function button for 10 seconds or until a distinctive three-tone sound will be heard and at the same time the red and blue indicator will alternately blink.

a. ACTIVATING THE BLUETOOTH

You must activate your Bluetooth to establish a Bluetooth connection between your mobile phone and other Bluetooth devices.

1. Press *Menu*. Scroll to *Connectivity*, **SELECT**. *Bluetooth*, **SELECT**.
2. Choose *On*, **SELECT**. An icon will appear on the display on the standby mode.
3. Continue pressing *Back* button to exit the *Menu*.

QUICK ACCESS:

Press *Menu* followed by the sequence of numbers below.

	Connectivity	Bluetooth	Select	On	Select
8910i	10	1	1	1	1

b. PAIRING TO THE CELLULAR PHONE

1. Bring the cellular phone at about 20 cm from the headset.
2. From the OFF state, press the multi-function button for 10 seconds or until a distinctive three tone sound will be heard and at the same time the red and blue indicator will alternately blink. This indicates that the headset is now ready for pairing.
3. Press *Menu*. Scroll to *Connectivity*, **SELECT**. *Bluetooth*, **SELECT** and scroll to *Search for audio accessories*, **SELECT**. The phone is now searching for Bluetooth devices. **SELECT** the headset. The phone will initiate connection with the headset.

QUICK ACCESS (for step 3):

Press *Menu* followed by the sequence of numbers below.

	Connectivity	Bluetooth	Search for audio accessories
8910i	10	1	2

4. Enter "0000" as the passcode then press **OK**. The phone is now connected with the headset.
5. Continue pressing the *Back* button to exit the *Menu*.

The headset is paired and ready to use. An icon will be displayed during the standby mode indicating that the headset is linked with the phone.

Note: Once paired, the headset and the phone have simultaneous connection with each other (keypad tones can be heard on the headset every time the keypad is pressed).

c. AUTO ACCEPT MODE

The auto accept mode allows the Bluetooth function to be turned on automatically whenever the user starts sending information such as answering or making a call via the Bluetooth headset.

1. Press *Menu*. Scroll to *Connectivity*, **SELECT**. *Bluetooth*, **SELECT**. Scroll to *View paired devices*, **SELECT**.
2. Select the headset and press **OPTIONS**. Scroll to *Request conn. authorisation*, **SELECT**. *No*, **SELECT**.
3. Continue pressing *Back* button to exit the *Menu*.

QUICK ACCESS:

Press *Menu* followed by the sequence of numbers below.

	Connectivity	Bluetooth	View paired devices	Select
8910i	10	1	4	Options

d. ANSWERING/RECEIVING A CALL

When the phone is receiving a call, a ring tone will be heard on the headset as well as on the phone.

1. Press the multi-function button down once to answer the call.
2. End the call by pressing the button again.

Note: Cell phone buttons can also be used to answer a call but audio is still transferred to the headset.

e. **MAKING A CALL with the headset on**

▼ **Normal dialing**

1. Enter the contact number and send. As you dial, audio and the keypad tones can be heard on the headset simultaneously but not on the phone.
2. Press the multi-function button to hang-up and terminate the call.

Note: If the call is terminated using the cellular phone, a tone will be heard on the headset indicating that the call has been terminated.

▼ **Voice dialing**

Refer to step g for the procedure when recording for voice dialing.

1. Press the multi-function button once to activate the voice dialing.
2. A beep will then be heard on the headset prompting the user to say the name of the person to call.
3. Say the name. The name will be played back to you. The phone will then place the call automatically. In case the cellular phone does not recognize the name spoken, the steps above may be repeated.
4. Press the button again to terminate the call.

▼ **Redialing**

Press quickly the multi-function button twice to redial the last number.

f. **REJECTING A CALL**

Press the multi-function button to reject the incoming call.

g. **RECORDING FOR VOICE DIALING**

Use your phone when recording voice dialing.

1. From standby mode, press arrow up or down.
2. Find a contact name to which you want to add a voice tag. Press *Details* button. The phone number will be displayed.
3. Press *Options* button. *Add voice tag*, **SELECT**. Press *Start*, and say the name clearly. *Voice tag saved* is displayed indicating that the voice tag has been saved.
4. In case you wish to change your recorded voice, press *Names*, *Voice tags*, **SELECT**. Scroll to the name whom you want to change the voice tag then press **Options**. *Change*, **SELECT**. Follow the instructions.
5. Continue pressing *Back* button to exit.

Note: Noisy environment could affect voice recognition. Record voice in a quiet environment.