

USING WITH MOTOROLA V600

ACTIVATING THE BLUETOOTH

You must activate the Bluetooth feature of your phone to be able to establish a Bluetooth connection between your phone and your SuperTooth II kit as well as with other Bluetooth devices.

1. Press **≡** key to access Main Menu >**Settings** >**Connection** >**Bluetooth Link** >**Setup**.
2. Scroll to **Power: Off** > CHANGE > **ON**.
3. Press **Back** or **Exit** as many times as needed to return to standby mode.

PAIRING TO THE CELLULAR PHONE (Not possible while charging the SuperTooth II)

Pairing will create a link or connection between your two Bluetooth devices - the SuperTooth II kit and your phone.

1. This SuperTooth II kit supports either **Handsfree** or **Headset** pairing mode. First, refer to **Compatibility Table** for suggested pairing modes to be able to determine what pairing mode is best for your phone. **Handsfree** and **Headset** profile differs in pairing procedure. (*Note: In the Compatibility Table, you can find that Motorola V600 belongs to Handsfree Profile.*) Proceed with the instructions.
2. Bring the mobile phone at about 20cm from SuperTooth II.
3. The SuperTooth II is initially off. Turn it on by flipping up the **Swivel Arm(1)** to 55° position. The **Bluetooth Indicator(9)** will glow (*blue blink*).
4. Simultaneously press the **Reject Button (2)** and **Pick-Up/Hang-Up Button (7)** for about 10seconds. A distinctive tone will be heard and the Bluetooth Indicator LED will change from blinking blue to alternate blinking red and blue. SuperTooth II is now in **Handsfree Pairing Mode**.
5. While the kit is at pairing mode, access the Bluetooth menu of your phone. Press **≡** key to access Main Menu. Scroll to **Settings** > **Connection** > **Bluetooth Link** > **Hands-free** > [**Look for devices**], SELECT. The phone will then scan the device to be added.
6. On the scan results, choose the name of this Handsfree Kit, **SELECT**. A question "*Bond with ... (device name)?*" appears. Press **YES**.
7. Enter Bluetooth passkey "0000" then press **ok**. If pairing is successful, a remark "**Connected(device name)**" appears. The phone exits automatically.

The SuperTooth is now ready to use.

ANSWERING / ENDING A CALL

When you receive a call, ring tone will be heard simultaneously on the SuperTooth II and on the phone or on the SuperTooth II only (*depending on your phone model*).

1. Just shortly press **Pick-Up/Hang-Up Button(7)** to answer the call.
2. When communication is over, press the **Pick-Up/Hang-Up Button(7)** to end the call.

MAKING A CALL

Normal dialing

Enter the contact number and send. Normally, audio will be on the kit.

Note: With some phones like Siemens S55; Panasonic X70, audio is always on the phone during an outgoing call. You will need to press Pick-Up/Hang-Up Button(7) to transfer the audio to your kit. (Also, refer to "Compatibility Table" for other helpful remarks.)

Voice dialing

Note: Voice dialing entries must be stored in the phone's memory (not on the SIM card!).

1. First, you have to turn on the voice dial function and record for a "*voice command*" or "*voice tag*" in your phone. Record your voice command in a quiet place so that only your voice will be recorded on the phone.
2. **Activating the Voice Dial Function:** Press **≡** key to access Main Menu. Scroll to **Settings**, SELECT. Scroll to **Headset**, SELECT.
3. Choose **Voice Dial**, CHANGE. Choose **ON**, SELECT.
4. Press **Back** or **Exit** as many times as needed to return to standby mode.

5. **Recording for Voice dial:** Press **≡** key to access Main Menu. Scroll to **Phonebook**, SELECT.
6. Choose a contact which you want to make a *voice dial*, press **VIEW** then **EDIT**.
7. On the **Entry Details** window, scroll to "**Store To: _____**", >press **CHANGE** key > Choose **Phone**. (This is storing the number to phone memory).
8. Scroll to "**Voice Name: _____**" then press **RECORD**. Follow instructions on the screen.
9. *Note: If recording is successful, an icon will appear next to Voice Name.*
10. Press **DONE**.
11. Press **Back** or **Exit** as many times as needed to return to standby mode.
Note: In the listed names of your Phonebook, voice dial icon now appears next to a name which has a "Voice Name". This indicates that you can contact this person via "voice dial".

When recording is done, execute voice dialling in your kit by proceeding with the instructions.

12. Shortly press **Pick-Up/Hang-Up Button(7)**.
13. A beep will then be heard on the SuperTooth II prompting the user to say a voice name or voice tag of a person to call.
14. Say the name. The name will be played back to you (audio on kit). The phone will then place the call automatically.

REDIALING (Handsfree profile only)

Make a long press on the **Pick-Up/Hang-Up Button(7)**. Audio will be on the SuperTooth II.

AUDIO TRANSFER

Kit to Phone

Flip down the **Swivel Arm (1)** to 0° position (or turn-off the unit). This will automatically transfer the audio from the kit to the phone.

Phone to Kit

For Nokia Phones:

Flip up the **Swivel Arm** from 0° to 55° or 210° positions. (or turn-on the unit). This will automatically transfer the audio from phone to kit.

For Other Phone Models:

Flip the **Swivel Arm** up from 0° to 55° or 210° positions (or turn-on the unit).

Then press shortly the **Pick-Up/Hang-Up Button(7)**. The audio will be transferred from the phone to the kit.

REJECTING A CALL (Handsfree Profile only)

Press **Reject Button(2)** to reject an incoming call.

SETTING THE VOLUME

Set the volume using the **Volume Control(11)**.

1. Turn it clockwise to increase the volume.
2. Turn it counter clockwise to decrease.

Note: If the volume set is too high, it can cause feedback (whistling sound), echo, or background noise during calls on some cell phones.