


## USING WITH MOTOROLA V80


### ACTIVATING THE BLUETOOTH

You must activate the Bluetooth feature of your phone to be able to establish a Bluetooth connection between your phone and your SuperTooth II kit as well as with other Bluetooth devices.

1. Press the joystick or  key to access Main Menu > **Settings** > **Connection** > **Bluetooth Link** > **Setup**.
2. Scroll to **Power: \_\_\_\_\_** > CHANGE > **ON**.
3. Press **Back** or **Exit** as many times as needed to return to standby mode.

### PAIRING TO THE CELLULAR PHONE (Not possible while charging the SuperTooth II)

Pairing will create a link or connection between your two Bluetooth devices - the SuperTooth II kit and your phone.

1. This SuperTooth II kit supports either **Handsfree** or **Headset** pairing mode. First, refer to **Compatibility Table** for suggested pairing modes to be able to determine what pairing mode is best for your phone. **Handsfree** and **Headset** profile differs in pairing procedure. (Note: In the **Compatibility Table**, you can find that *Motorola V80 belongs to Handsfree Profile*.) Proceed with the instructions.
2. Bring the mobile phone at about 20cm from SuperTooth II.
3. The SuperTooth II is initially off. Turn it on by flipping up the **Swivel Arm(1)** to 55° position. The **Bluetooth Indicator(9)** will glow (*blue blink*).
4. Simultaneously press the **Reject Button (2)** and **Pick-Up/Hang-Up Button (7)** for about 10seconds. A distinctive tone will be heard and the Bluetooth Indicator LED will change from blinking blue to alternate blinking red and blue. SuperTooth II is now in **Handsfree Pairing Mode**.
5. While the kit is at pairing mode, access the Bluetooth menu of your phone. Press joystick or  to access Main Menu. Scroll to **Settings** > **Connection** > **Bluetooth Link** > **Hands-free** > [**Look for devices**], SELECT. The phone will then scan the device to be added.
6. On the scan results, choose the name of this Handsfree Kit, **SELECT**. A question “Bond with ... (device name)?” appears. Press **YES**.
7. Enter Bluetooth passkey “0000” then press **ok**. If pairing is successful, a remark “Connected to...” appears. The phone exits automatically.

The SuperTooth is now ready to use.

### ANSWERING / ENDING A CALL

When you receive a call, ring tone will be heard simultaneously on the SuperTooth II and on the phone or on the SuperTooth II only (*depending on your phone model*).

1. Just shortly press **Pick-Up/Hang-Up Button(7)** to answer the call.
2. When communication is over, press the **Pick-Up/Hang-Up Button(7)** to terminate the call.

### MAKING A CALL


#### Normal dialing


Enter the contact number and send. Normally, audio will be on the kit.

**Note: With some phones like Siemens S55; Panasonic X70, audio is always on the phone during an outgoing call. You will need to press Pick-Up/Hang-Up Button(7) to transfer the audio to your kit. (Also, refer to “Compatibility Table” for other helpful remarks.)**

#### Voice dialing

**Note: Voice dialing entries must be stored in the phone's memory (not on the SIM card!).**

1. First, you have to turn on the voice dial function and record for a “voice command” or “voice tag” in your phone. Record your voice command in a quiet place so that only your voice will be recorded on the phone.
2. **Activating the Voice Dial Function:** Press the joystick or  key to access Main Menu. Scroll to **Settings**, SELECT. Scroll to **Headset**, SELECT.
3. Choose **Voice Dial**, CHANGE. Choose **ON**, SELECT.
4. Press **Back** or **Exit** as many times as needed to return to standby mode.

5. **Recording for Voice dial:** Press the joystick or  key to access Main Menu. Scroll to **Phonebook**, SELECT.
6. Choose a contact which you want to make a *voice dial*, press **VIEW** then **EDIT**.
7. On the **Entry Details** window, scroll to “**Store To: \_\_\_\_\_**”, >press **CHANGE** key > Choose **Phone**. (This is storing the number to phone memory).
8. Scroll to “**Voice Name: \_\_\_\_\_**” then press **RECORD**. Follow instructions on the screen.
9. *Note: If recording is successful, an icon will appear next to Voice Name.*
10. Press **DONE**.
11. Press **Back** or **Exit** as many times as needed to return to standby mode.  
*Note: In the listed names of your Phonebook, voice dial icon now appears next to a name which has a “Voice Name”. This indicates that you can contact this person via “voice dial”.*

When recording is done, execute voice dialling in your kit by proceeding with the instructions.

12. Shortly press **Pick-Up/Hang-Up Button(7)**.
13. A beep will then be heard on the SuperTooth II prompting the user to say a voice name or voice tag of a person to call.
14. Say the name. The name will be played back to you (audio on kit). The phone will then place the call automatically.

### REDIALING (Handsfree profile only)

Make a long press on the **Pick-Up/Hang-Up Button(7)**. Audio will be on the SuperTooth II.

### AUDIO TRANSFER

#### Kit to Phone

Flip down the **Swivel Arm (1)** to 0° position (or turn-off the unit). This will automatically transfer the audio from the kit to the phone.

#### Phone to Kit

##### For Nokia Phones:

Flip up the **Swivel Arm** from 0° to 55° or 210° positions. (or turn-on the unit). This will automatically transfer the audio from phone to kit.

##### For Other Phone Models:

Flip the **Swivel Arm** up from 0° to 55° or 210° positions (or turn-on the unit).

Then press shortly the **Pick-Up/Hang-Up Button(7)**. The audio will be transferred from the phone to the kit.

### REJECTING A CALL (Handsfree Profile only)

Press **Reject Button(2)** to reject an incoming call.

### SETTING THE VOLUME

Set the volume using the **Volume Control(11)**.

1. Turn it clockwise to increase the volume.
2. Turn it counter clockwise to decrease.

*Note: If the volume set is too high, it can cause feedback (whistling sound), echo, or background noise during calls on some cell phones.*