



## USING WITH SIEMENS SX1



### ACTIVATING THE BLUETOOTH

You must activate the Bluetooth feature of your mobile phone to establish Bluetooth connection between it and other Bluetooth devices.

1. Press Menu key  > **Setup > Bluetooth.**
2.  is highlighted. Press **Options > Change.**
3. Choose **On** and press **Ok**.
4. Continue pressing **Exit/Back** key until you finally Exit.



### PAIRING TO THE CELLULAR PHONE (Not possible while charging the SuperTooth II)

Pairing will create a link or connection between your two Bluetooth devices - the SuperTooth II kit and your phone.

1. This SuperTooth II kit supports either **Handsfree** or **Headset** pairing mode. First, refer to **Compatibility Table** for suggested pairing modes to be able to determine what pairing mode is best for your phone. **Handsfree** and **Headset** profile differs in pairing procedure. (Note: In the *Compatibility Table*, you can find that Siemens SX1 belongs to Handsfree Profile.) Proceed with the instructions.
2. Bring the mobile phone at about 20cm from SuperTooth II.
3. The SuperTooth II is initially off. Turn it on by flipping up the **Swivel Arm(1)** to 55° position. The **Bluetooth Indicator(9)** will glow (blue blink).
4. Simultaneously press the **Reject Button (2)** and **Pick-Up/Hang-Up Button (7)** for about 10seconds. A distinctive tone will be heard and the Bluetooth Indicator LED will change from blinking blue to alternate blinking red and blue. SuperTooth II is now in **Handsfree Pairing Mode.**
5. While the kit is at pairing mode, press Menu key  > **Setup > Bluetooth.**
6.  will be displayed. Sway joystick to the right to open **Paired devices** window.
7. Press **Options > New paired device.**  
The phone will then start to search for other Bluetooth devices until it displays them in the list.
8. Select SuperTooth II.
9. When the phone asks for the passcode, enter **0000** then press **OK**. Wait for a moment until pairing is complete.
10. Under **Paired devices**, highlight again the paired device (SuperTooth II) then press **Options > Connect.**
11. Wait until the statement **“Connected to SuperTooth II ... “** appears.
12. Continue pressing **Exit/Back** key until you finally Exit.

*The Hands-free Kit is paired and ready to use.*

### AUTO ACCEPT MODE

1. Press Menu key  > **Setup > Bluetooth.**
2.  is highlighted.
3. Sway the joystick to the right to view **Paired devices** window.
4. Highlight SuperTooth II and press **Options > Set as authorised.**
5. A statement **“Connections will take place without confirmation. Continue?”** appears. Press **Yes.**
6. Continue pressing **Exit/Back** key until you finally Exit.

### ANSWERING / ENDING A CALL

When you receive a call, ring tone will be heard simultaneously on SuperTooth II and on the phone or on the SuperTooth II only (depending on your phone model).

1. Just shortly press **Pick-Up/Hang-Up Button(7)** to answer the call.
2. When communication is over, press the **Pick-Up/Hang-Up Button(7)** to terminate the call.

### MAKING A CALL


#### **Normal dialing**

Enter the contact number and send. Normally, audio will be on the kit.

**Note: With some phones like Siemens S55; Panasonic X70, audio is always on the phone during an outgoing call. You will need to press Pick-Up/Hang-Up Button(7) to transfer the audio to your kit. (Also, refer to “Compatibility Table” for other helpful**

#### **Voice dialing**

**Note: Voice dialing entries must be stored in the phone's memory (not on the SIM card!).** First, you have to turn on the voice dial function and record for a “voice command” or “voice tag” in your phone. **Note: Record a voice in quiet environment. Voice tags are sensitive to loud background noise.**

1. **RECORDING FOR VOICE DIALING:** Press Menu Key  > **Contacts.**
2. Choose and Open an entry you want to make a voice dial.
3. Press down the joystick. Name and number of selected entry will be displayed. Press **Options > Add voice tag.**
4. Follow the instructions displayed on screen. **Note: You may use any word or just use the person's name for a voice tag.**
5. Wait until the word is repeated and automatically saved by the phone.
6. Continue pressing **Exit/Back** key until you finally Exit.

When recording is done, execute voice dialing on your kit by proceeding with the instructions.

7. Shortly press **Pick-Up/Hang-Up Button(7).**
8. A beep will then be heard on the SuperTooth II prompting the user to say a voice name or voice tag of a person to call.
9. Say the name. The name will be played back to you (audio on kit). The phone will then place the call automatically.

### REDIALING (Handsfree profile only)

Make a long press on the **Pick-Up/Hang-Up Button (7)**. Audio will be on the SuperTooth II.

### AUDIO TRANSFER

#### **Kit to Phone**

Flip down the **Swivel Arm (1)** to 0° position (or turn-off the unit). This will automatically transfer the audio from the kit to the phone.

#### **Phone to Kit**

For Nokia Phones:

Flip up the **Swivel Arm** from 0° to 55° or 210° positions. (or turn-on the unit). This will automatically transfer the audio from phone to kit.

For Other Phone Models:

Flip the **Swivel Arm** up from 0° to 55° or 210° positions (or turn-on the unit).

Then press shortly the **Pick-Up/Hang-Up Button(7)**. The audio will be transferred from the phone to the kit.

### REJECTING A CALL (Handsfree Profile only)

Press **Reject Button(2)** to reject an incoming call.

### SETTING THE VOLUME

Set the volume using the **Volume Control(11).**

1. Turn it clockwise to increase the volume.
2. Turn it counter clockwise to decrease.

**Note: If the volume set is too high, it can cause feedback (whistling sound), echo, or background noise during calls on some cell phones.**